

Lehto



Adjustable light source
Sorgente orientabile

White Bianco 1 x 20W - 48V

- 2700K CRI 97 - 1800 lm
- | | |
|-------|-----------------------|
| 53380 | ON-OFF/PWMDimmable |
| 59380 | 0-10 / 1-10V Dimmable |
| 55380 | DALI 2 Dimmable |

- 3000K CRI 97 - 1900 lm
- | | |
|-------|-----------------------|
| 53381 | ON-OFF/PWMDimmable |
| 59381 | 0-10 / 1-10V Dimmable |
| 55381 | DALI 2 Dimmable |

Black Nero 1 x 20W - 48V

- 2700K CRI 97 - 1800 lm
- | | |
|-------|-----------------------|
| 53580 | ON-OFF/PWMDimmable |
| 59580 | 0-10 / 1-10V Dimmable |
| 55580 | DALI 2 Dimmable |


- 3000K CRI 97 - 1900 lm
- | | |
|-------|-----------------------|
| 53581 | ON-OFF/PWMDimmable |
| 59581 | 0-10 / 1-10V Dimmable |
| 55581 | DALI 2 Dimmable |

To be completed with lenses
Da completare con ottiche

- | | |
|-------|-------------|
| 51102 | 30° |
| 51104 | 40° |
| 51106 | 60° |
| 51108 | Oval |
| 51110 | Rectangular |
| 51112 | Wallwasher |

ATTENTION! If used with track inserted in recessed formwork 16325-16525, add DS to the code when ordering [e.g. 53380DS].

ATTENZIONE! Se utilizzato con binario inserito in cassaforma arretrata 16325-16525, aggiungere DS al codice in fase d'ordine [es. 53380DS].



IP20  Kg 0.80

In the DALI 2 version, the BOB sources can be controlled in One by One mode.
By using the Casambi Voice 40219 device, it is possible to connect DALI 2 sources to the Casambi environment in One by One mode.
In the 0-10V, 1-10V version they can be dimmed without using any additional dimmer (broadcast mode).
In the PWM version, through the use of the PWM dimmers 40209-40215-40216-40217-40218, in combination with the non-dimmable power supplies 40205-40210-40213, allows maximum compatibility with the different dimming systems: 0-10V, 1-10V, Push, potentiometer, CUT PHASE, DALI 1, DALI 2, Casambi, Amazon Alexa, Google Home and Matter [Apple Home]. The sources are controlled in broadcast mode.

Nella versione DALI 2, le sorgenti BOB possono essere controllate in modalità One by One.
Attraverso l'utilizzo del dispositivo Casambi Voice 40219 è possibile collegare le sorgenti DALI 2 all'ambiente Casambi in modalità One by One.
Nella versione 0-10V, 1-10V possono essere dimmerate senza l'utilizzo di alcun dimmer aggiuntivo (modalità broadcast).
Nella versione PWM, attraverso l'utilizzo dei dimmer PWM 40209-40215-40216-40217-40218, in abbinamento agli alimentatori non dimmerabili 40205-40210-40213, consentono la massima compatibilità ai differenti sistemi di dimmerazione: 0-10V, 1-10V, Push, potenziometro, taglio di fase, DALI 1, DALI 2, Casambi, Amazon Alexa, Google Home e Matter [Apple Home]. Le sorgenti sono controllate in modalità broadcast.

BOB is a LED spot with double joint that allows an inclination of 90° on the horizontal plane and a rotation of 360° around the vertical axis. Aluminum structure and heat sink. Easy replacement of secondary lens. Optics: 30°, 40°, 60°, oval, rectangular, Wallwasher. Different shade LEDs [2700K, 3000K and others on request]. BOB sources can be connected to different types of dimming. Photometric measure LETROH.com

BOB è uno spot LED con doppio snodo che permette un'inclinazione di 90° sul piano orizzontale e una rotazione di 360° attorno all'asse verticale. Struttura e dissipatore in alluminio. Facile sostituzione dell'ottica secondaria. Ottiche: 30°, 40°, 60°, ovale, rettangolare, Wallwasher. LED di differenti tonalità [2700K, 3000K e altre su richiesta]. Le sorgenti BOB possono essere collegate ad impianti di differenti tipologie di dimmerazione. Curve fotometriche LETROH.com



LETROH Srl

Via Cadorna 15
20073 Opera [Milano] Italia

contact@letroh.com
letroh.com



ELECTROSOPHY O5